WIRE COLOR SCHEME
BLACK — LINE VOLTAGE
RED — AC CONTROL
WHITE — AC GROUNDED
CIRCUIT CONDUCTOR
BLUE — DC CONTROL
GREEN — CHASSIS GROUND

TERMINAL IDENTIFICATION

X - DRIVE TERMINAL

CUSTOMER TERMINAL

EARTH GROUND EARTH GROUND AC MOTOR *CUSTOMER SUPPLIED L1 (L1) (T1) 1L1 BLK 3L1 L1/R/91 INPUT T1/U/96 F16A POWER | T16B| 3L2 | L1/R/91 | L2/S/92 ADJUSTABLE FREQUENCY BRANCH L2 (L2) (T2) 1L2 BLK T2 3 PH, 600V, T2/V/97 DRIVE |F16E| 3L3 | L2/3/92 | L3/T/93 CIRCUIT L3 (L3) (T3) 1L3 BLK PROTECTION T3/W/98 (AFD) (SEE NOTE 3) DRIVE INPUT FUSES MAIN DISCONNECT EARTH GROUND GRN * CUSTOMER RUN -18 D IN +24 VDC 29-163 RED 100 WHT CUSTOMER DRY CONTACT RATINGS F12 -13 +24VDC X2 X3 250V 115VAC T2 COM 20 BLU RELAY CONTACT RATING 27 D IN (12) 5 (11) TS1 HEATER (SET: 65° F) CUSTOMER'S SAFETY 'J1' 5A @ 120VAC CR6 1/10 HP @ 120VAC INTERLOCK (SEE NOTE 4) 12 +24VDC 2) FAN 1 (SET: 80° F) (9) (5) (23) (24) TS1 TB2 VLT FAN 2 ADJUSTABLE 53_3 FREQUENCY DRIVE (AFD) DRIVE RUN CR6 (10) (2)

NOTES:

1. * INDICATES COMPONENTS NOT SUPPLIED BY MANUFACTURER.

- 2. REFER TO THE INSTALLATION AND OPERATION MANUAL FOR DRIVE FUNCTIONS AND PARAMETER SETTINGS.
- 3. BRANCHCIRCUIT PROTECTION, INPUT POWER AND MOTOR WIRING MUST BE SELECTED IN ACCORDANCE WITH THE N.E.C., ANY APPLICATION LOCAL CODES AND THE LOAD CURRENT RATING.
- 4. REPLACE JUMPER 'J1' WITH NORMALLY CLOSED SAFETY INTERLOCK CONTACT AS NECESSARY.
- 5. PANEL MAY REQUIRE DERATING, CONSULT DRIVE MANUAL OR FACTORY FOR FOLLOWING CONDITIONS:
- 5.1. HIGHER SWITCHING FREQUENCY THAN DRIVE DEFAULT
- 5.2. HIGHER THAN PANEL LISTED AMBIENT TEMPERATURES
- 5.3. ELEVATION ABOVE 3300 FEET (1000 METERS)
- 5.4. LONG MOTOR LEAD LENGTHS

THE FOLLOWING TABLE LISTS THE PARAMETERS THAT ARE SET DIFFERENT FROM THE DRIVE DEFAULT SETTINGS. ADDITIONAL PARAMETER SETTINGS MAY BE REQUIRED FOR YOUR APPLICATION.

WARNING!

DRIVE PARAMETER SETTINGS

PARAMETER #	NAME	SETTING	VALUE			
0-02	MOTOR SPEED UNIT	1	HZ			
0-03	REGIONAL SETTINGS	1	NORTH AMERICA			
1-03	TORQUE CHAR.	3	AUTO ENERGY OPTIM VT			
5-02	TERMINAL 29 TYPE	1	OUTPUT			
5-31	TERMINAL 29	5	RUNNING			
14-20	RESET MODE	13	INFINITE AUTO REST			

В			-NOTICE-	DRN	NAME		NEMA 3R,600V,NE			THE TRANE COMPANY	
А	SP10119	11/10	THIS DRAWING IS PROPRIETARY AND SHALL NOT BE COPIED OR ITS CONTENTS DISCLOSED TO OUTSIDE PARTIES WITHOUT THE WRITTEN CONSENT OF THE TRANE COMPANY	D TM	,MAIN DISC, DRIVE FUSE .SINGLE MOTOR.2 FAN				A DIVISION OF AMERICAN STANDARD INC.		
DR	SP10076	09/10			APR	MODEL	, ,				
REV	ECN	DATE		D TM	MODEL	TR200	PAGE <u>1</u> OF <u>1</u>	SIZE	DWG 18	35B3924	